



EdgeAccess' Circle the Wagons Kit is preconfigured to facilitate joining the forces of communications in minutes. An integrated patch panel includes (1) external 11dbi wireless tripod antenna jack for the wireless WAN, (1) smaller antenna for local access point, (1) wired WAN port, (4) ethernet switch ports for connecting external wired devices, and (2) RJ11 external fax, modem, phone ports, and AC power connector.

## Getting Started

- Plug in WAN port to wired network OR connect wireless to the EDICs trailer.
- Connect antennas to patch panel
- Connect Power Cord (included) between patch panel and AC power source. If AC power is unavailable, connect inverter to vehicle's DC outlet and turn toggle switch on. Note: leave vehicle running so as not to run down battery.



## Device Configuration via the Telephone Handset

Enter a key sequence from the list below to set the desired WAN and LAN parameters. (When delivered from the factory, WAN will be the primary ethernet device (eth0), LAN will be the secondary (eth1) or wireless device (wlan0)). When entering IP addresses and netmasks on the dial pad, use the \* (asterisk or star button) to indicate a . (dot) – *192.168.10.5 would be entered using 192\*168\*10\*5*

Always signal the end of the entry with a # and hang up the phone. Repeat for other set ups as needed.

**WAN Static IP Address:**      \*\*1 <IP Address> #  
**WAN Netmask:**                \*\*2 <Netmask> #  
**WAN Gateway:**                \*\*3 <Gateway IP> #  
**WAN Get dynamic IP Address**    \*\*4 #

**LAN Static IP Address:**        \*\*5 <IP Address> #  
**LAN Netmask:**                \*\*6 <Netmask> #  
**LAN Gateway:**                \*\*7 <Gateway IP> #  
**LAN Get dynamic IP Address:**    \*\*8 #

**RESET Default Configuration:**    \*\*00  
**WAN Wireless IP:**                192.168.20.1  
**WAN Wired IP:**                    192.168.10.1

**LAN Wireless IP:**                172.16.40.1  
**LAN Wired IP:**                    172.16.40.1

**Wireless AP ESSID:**            CTW01

**Hostname:**                        CTW01

**BB4-Line 1:**                    813.549.2250  
**BB4-Line 2:**                    813.549.2251

**HipSIP 1:**                        813.549.2254  
**HipSIP 2:**                        813.549.2255